



JFER SERIES OPERATING VOLTAGES/POWER

24VDC

Item	Model	Voltage	Rated Current (A)	Locked Current (A)	Power	Time
1	JFER-003	DC24V	0.56	0.74	8W	20S
1	JFER-005	DC24V	1.28	4.08	10W	30S
2	JFER-008	DC24V	1.69	4.08	10W	30S
3	JFER-010	DC24V	2.24	5.42	15W	60S
4	JFER-015	DC24V	2.43	5.42	15W	60S
5	JFER-020	DC24V	3.78	10.2	60W	30S
6	JFER-030	DC24V	5.25	10.2	60W	30S
7	JFER-040	DC24V	5.92	10.2	60W	30S
8	JFER-060	DC24V	7.13	10.2	60W	40S
9	JFER-080	DC24V	9.78	19.8	120W	40S
10	JFER-100	DC24V	13.4	19.8	120W	40S
11	JFER-160	DC24V	11.5	19.8	120W	60S
12	JFER-200	DC24V	12.1	19.8	120W	60S
13	JFER-300	DC24V	13.2	19.8	120W	120S
14	JFER-400	DC24V	15.8	21.4	120W	200S
15	JFER-500	DC24V	16.5	21.4	120W	200S

24VDC

Item	Model	Voltage	Rated Current (A)	Locked Current (A)	Power	Time
1	JFER-005	DC24V	1.65	4.08	10W	15S
2	JFER-010	DC24V	2.56	5.42	15W	15S
3	JFER-015	DC24V	2.95	5.42	15W	15S
4	JFER-020	DC24V	4.52	10.2	60W	15S
5	JFER-030	DC24V	5.76	10.2	60W	15S
6	JFER-040	DC24V	6.27	10.2	60W	15S
7	JFER-060	DC24V	8.52	10.2	60W	15S



JFER SERIES OPERATING VOLTAGES/POWER

120VAC

Item	Model	Voltage	Rated Current (A)	Locked Current (A)	Power	Time
1	JFER-003	AC120V	0.47	0.57	8W	20S
2	JFER-005	AC120V	0.36	0.69	10W	30S
3	JFER-008	AC120V	0.42	0.69	10W	30S
4	JFER-010	AC120V	0.67	0.78	15W	30S
5	JFER-015	AC120V	0.73	0.78	15W	40S
6	JFER-020	AC120V	0.79	1.34	60W	30S
7	JFER-030	AC120V	0.83	1.34	60W	30S
8	JFER-040	AC120V	0.88	1.34	60W	30S
9	JFER-060	AC120V	1.12	1.34	60W	40S
10	JFER-080	AC120V	1.86	3.56	90W	40S
11	JFER-100	AC120V	2.23	3.56	90W	40S
12	JFER-160	AC120V	1.56	3.56	90W	60S
13	JFER-200	AC120V	1.62	3.56	90W	60S
14	JFER-300	AC120V	1.88	3.56	90W	120S
15	JFER-400	AC120V	1.92	3.56	90W	200S
16	JFER-500		2.13	3.56	90W	200S

120VAC

Item	Model	Voltage	Rated Current (A)	Locked Current (A)	Power	Time
1	JFER-010	AC120V	0.68	0.78	15W	15S
2	JFER-020	AC120V	0.82	1.34	60W	15S
3	JFER-030	AC120V	0.86	1.34	60W	15S
4	JFER-040	AC120V	0.95	1.34	60W	15S
5	JFER-060	AC120V	1.23	1.34	60W	15S
6	JFER-080	AC120V	2.12	3.56	90W	15S
7	JFER-100	AC120V	2.35	3.56	90W	15S